

**SEMICONDUCTOR INTEGRATED CIRCUIT DEVICE,
PROGRAM DELIVERY METHOD, AND PROGRAM DELIVERY SYSTEM**

BACKGROUND OF THE INVENTION

The present invention relates to a semiconductor LSI having the function of
5 decrypting an encrypted program and executing the decrypted program which is mounted
on information equipment or the like. More particularly, it relates to a processing system
and method for encrypting a program and delivering the encrypted program from a device
at a program owner to a device at a program user.

With the widespread use of information equipment capable of rewriting a program
10 or executing a user program, a system for preventing illegal copying of software has been
devised in recent years. In a method in which a program is encrypted and delivered,
provision has been made to prevent the copying of a program for decrypting the encrypted
program (hereinafter referred to as the "decryption program". For example, a decryption
program is disposed in the internal memory of an LSI from which it cannot be read from
15 the outside and the decrypted program is further protected from being read from the
outside (see, e.g., Japanese Laid-Open Patent Publication No. HEI 8-30558).

FIG. 18 is a block diagram showing a conventional semiconductor integrated
circuit device for executing an encrypted program.

The semiconductor integrated circuit device 1 shown in FIG. 18 has: a CPU 3;
20 internal memories 4 and 5 for inputting/outputting data via an internal bus 7; a bus port 6
for controlling the inputting/outputting of data to and from the outside via an external bus
2; an I/O port 9 connected to the CPU 3 via an I/O bus 8; a memory port 10 for controlling
the internal RAM 5; and control registers 11 for controlling the memory port 10.

A decryption program for decrypting the encrypted program is stored in the
25 internal ROM 4. The encrypted program is read in the internal RAM 5 and decrypted in

accordance with the decryption program. The decrypted program is written in the internal RAM 5. The decrypted program written in the internal RAM 5 is protected from being read from the memory port 10 to the outside under the control of the control registers 11.

However, since the decryption program is kept in the LSI as described above, an internal nonvolatile memory should be provided in the LSI, which increases cost required for the LSI.

In addition, if a malicious program is encrypted, read in the LSI, and then executed, the decryption program may be transferred by the program to the outside and hacked. The use of the decryption program that has been hacked makes it possible to hack the encrypted program. Once the encrypted program is hacked, the LSI cannot be used any more since the decryption program cannot be changed.

A problem has also been encountered that an encryption program and an encryption strength cannot be selected by the encrypted program transferor.

SUMMARY OF THE INVENTION

It is therefore an object of the present invention to provide a lower-cost semiconductor integrated circuit device which allows a reduction in the probability that an encrypted program is hacked.

To solve the foregoing problems, a first semiconductor integrated circuit device according to the present invention comprises: a first memory for inputting and outputting data between a bus and itself; a second memory for inputting and outputting data between the bus and itself; a secret key holder for holding a secret key; a bus port for controlling access from outside to the bus; a CPU for storing an encrypted program and a decryption program in the first memory via the bus port, decrypting the encrypted program by using the decryption program and the secret key, and executing the decrypted program; and a controller for causing, when the encrypted program and the decryption program are stored

in the first memory, the bus port to disable access from the outside, enabling access to the first and second memories, and thereby transferring the encrypted program and the decryption program from the first memory to the second memory, disabling access to the first memory when the transfer is completed, and disabling access to the second memory when the decryption and the execution of the decrypted program are completed.

With the first semiconductor integrated circuit device according to the present invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked.

Preferably, the first semiconductor integrated circuit device according to the present invention further comprises: a secret key access port for controlling access from the CPU to the secret key holder, wherein the secret key access port enables access to the secret key holder when the transfer is completed and disables access to the secret key holder when the execution of the decrypted program is completed.

In the first semiconductor integrated circuit device according to the present invention, the CPU preferably includes a register and erases data stored in the register if the execution of the decrypted program is completed.

In the first semiconductor integrated circuit device according to the present invention, the controller preferably controls access to the first and second memories by controlling chip select signals to the first and second memories.

In the first semiconductor integrated circuit device according to the present invention, the controller preferably includes a flag storing portion for storing first and second flags, enables access to the first and second memories when the first flag is set,

disables access to the first memory when the first flag is reset and the second flag is set, and disables access to the second memory when each of the first and second flags is reset, the bus port preferably disables access from the outside when at least one of the first and second flags is set, and the CPU preferably sets the first and second flags when the encrypted program and the decryption program are inputted to the first memory, resets the first flag when the transfer is completed, and resets the second flag when the execution of the decrypted program is completed.

To solve the foregoing problems, a second semiconductor integrated circuit device according to the present invention comprises: a first memory for inputting and outputting data between a bus and itself; a second memory for inputting and outputting data between the bus and itself; a first memory port connected between the bus and the first memory to control access from the bus to the first memory; a second memory port connected between the bus and the second memory to control access from the bus to the second memory; a secret key holder for holding a secret key; a bus port for controlling access from outside to the bus; a CPU having a register, the CPU writing an encrypted program and a decryption program in the first memory via the bus port, decrypting the encrypted program by using the decryption program and the secret key, writing the decrypted program in the second memory, and executing the decrypted program; and a controller for causing, when the writing to the first memory is completed, the bus port to disable access from the outside to the bus, causing the first memory port to disable the writing to the first memory, and causing the second memory port to enable access to the second memory and causing, when the execution of the decrypted program is completed, the CPU to erase data stored in the register and disable access to the secret key holder, while causing the second memory port to disable access to the second memory.

With the second semiconductor integrated circuit device according to the present

invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked.

To solve the foregoing problems, a third semiconductor integrated circuit device according to the present invention comprises: a first memory for inputting and outputting data between a bus and itself; a second memory for inputting and outputting data between the bus and itself; a memory port connected between the bus and the first memory to control access from the bus to the first memory; a secret key holder for holding a secret key; a bus port for controlling access from outside to the bus; a CPU having a register, the CPU writing an encrypted program and a decryption program in the first memory via the bus port, decrypting the encrypted program by using the decryption program and the secret key, writing the decrypted program in the second memory, and executing the decrypted program; and a controller including a memory initializer for erasing data in the second memory, the controller causing, when the wiring to the first memory is completed, the bus port to disable access from the outside to the bus and causing the memory port to disable the writing to the first memory and causing, when the execution of the decrypted program is completed, the CPU to erase data stored in the register and disable access to the secret key holder and causing the memory initializer to erase the data in the second memory.

With the third semiconductor integrated circuit device according to the present invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This

reduces the probability that the encrypted program is hacked.

To solve the foregoing problems, a fourth semiconductor integrated circuit device according to the present invention comprises: a first memory for inputting and outputting data between a bus and itself; a second memory for inputting and outputting data between the bus and itself; a secret key holder for holding a secret key; a decryption key holder for holding a decryption key; a bus port for controlling access from outside to the bus; a CPU including a register, the CPU performing first storage for storing the encrypted decryption key and a decryption key decryption program in the first memory via the bus port, performing first decryption for decrypting the encrypted decryption key by using the decryption key decryption program and the secret key, writing the decrypted decryption key in the decryption key holder, performing second storage for storing an encrypted program and a decryption program in the first memory, performing decryption for decrypting the encrypted program by using the decryption program and the decrypted decryption key, and executing the decrypted program; and a controller for causing, when the first storage to the first memory is completed, the bus port to disable access from the outside to the bus and enabling access to the first and second memories such that the encrypted decryption key and the decryption key decryption program are transferred from the first memory to the second memory, enabling, when the transfer is completed, access to the secret key holder and disabling access to the first memory; causing, when the first decryption is completed, the CPU to erase data stored in register and disable access to the secret key holder, while disabling access to the second memory, enabling access to the first memory, and causing the bus port to enable access from the outside to the bus, causing, when the second storage to the first memory is completed, the bus port to disable access from the outside to the bus and enabling access to the second memory such that the encrypted program and the decryption program are transferred from the first memory to the

second memory, enabling, when the transfer is completed, access to the decryption key holder and disabling access to the first memory, and causing, when the second decryption and the execution of the decrypted program are completed, the CPU to erase data stored in the register and disable access to the secret key holder and disabling access to the second
5 memory.

With the fourth semiconductor integrated circuit device according to the present invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed,
10 while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked. In addition, the encryption program and the encryption strength can be selected at the encrypted program transferor.

To solve the foregoing problems, a first program delivery method according to the present invention is a program delivery method for delivering a program between a first
15 device and a second device, the method comprising the steps of: transferring a public key from the second device to the first device; transferring a decryption program to the second device from the outside thereof; encrypting the program by using the public key in the first device and transferring the encrypted program to the second device; and decrypting the encrypted program by using a secret key corresponding to the public key and the
20 decryption program in the second device.

In accordance with the first program delivery method of the present invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the
25 program and data under decryption are not monitored from the outside. This reduces the

probability that the encrypted program is hacked.

To solve the foregoing problems, a second program delivery method according to the present invention is a program delivery method for delivering a program between a first device and a second device, the method comprising the steps of: transferring a public key
5 from the second device to the first device; encrypting a decryption key by using the public key in the first device and transferring the encrypted decryption key to the second device; decrypting the encrypted decryption key by using a secret key corresponding to the public key in the second device; encrypting the program by using an encryption key corresponding to the decryption key in the first device and transferring the encrypted
10 program to the second device; and decrypting the encrypted program by using the decrypted decryption key in the second device.

In accordance with the second program delivery method of the present invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is
15 achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked. In addition, the encryption program and the encryption strength can be selected at the encrypted program transferor.

To solve the foregoing problems, a first program delivery system according to the
20 present invention is a program delivery system for delivering a program, the system comprising: a first device and a second device, the first device encrypting the program by using a public key and transferring the encrypted program to the second device and the second device decrypting the program encrypted by the first device by using a secret key corresponding to the public key and a decryption program transferred from the outside of
25 the second device.

In accordance with the first program delivery system of the present invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked.

To solve the foregoing problems, a second program delivery system according to the present invention is a program delivery system for delivering a program, the system comprising: a first device and a second device, the first device encrypting a decryption key by using a public key, transferring the encrypted decryption key to the second device, encrypting the program by using an encryption key corresponding to the decryption key, and transferring the encrypted program to the second device, the second device decrypting the decryption key encrypted by the first device by using a secret key corresponding to the public key and decrypting the program encrypted by the first device by using the decrypted decryption key.

In accordance with the second program delivery system of the present invention, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked. In addition, the encryption program and the encryption strength can be selected at the encrypted program transferor.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG.1 is a block diagram for illustrating a structure of a semiconductor integrated circuit device in a first embodiment of the present invention;

FIG. 2 is a flow chart showing the procedure of decrypting an encrypted program;

FIG. 3 is a block diagram for illustrating a structure of a semiconductor integrated circuit device in a second embodiment of the present invention;

FIG. 4 is a flow chart showing the procedure of decrypting an encrypted program;

FIG. 5 is a block diagram for illustrating a structure of a semiconductor integrated circuit device in a third embodiment of the present invention;

FIG. 6 is a flow chart showing the procedure of decrypting an encrypted program;

FIG. 7 is a block diagram for illustrating a structure of a semiconductor integrated circuit device in a fourth embodiment of the present invention;

FIG. 8 is a flow chart showing the procedure of decrypting an encrypted decryption key;

FIG. 9 is a view showing correlations among the respective states of flags, a bus port, and chip select signals;

FIG. 10 is a flow chart showing the procedure of decrypting an encrypted program;

FIG. 11 is a view showing the transfer of a public key from a program user to a program developer;

FIG. 12 is a view showing the encryption of a decryption key;

FIG. 13 is a view showing the transfer of an encrypted decryption key from the program developer to the program user;

FIG. 14 is a view showing the decryption of an encrypted decryption key;

FIG. 15 is a view showing the encryption of a program;

FIG. 16 is a view showing the transfer of an encrypted program from the program developer to the program user;

FIG. 17 is a view showing the decryption of an encrypted program; and

FIG. 18 is a block diagram showing a structure of a conventional semiconductor integrated circuit device.

DETAILED DESCRIPTION OF THE INVENTION

Referring to the drawings, the individual embodiments of the present invention will be described herein below.

EMBODIMENT 1

FIG. 1 is a block diagram for illustrating a structure of a semiconductor integrated circuit device **101** in a first embodiment of the present invention.

As shown in FIG. 1, an encrypted program is transferred from a PC **128a** (corresponding to a first device) which is a device at a program developer to a program user via a PC **126**. In the semiconductor integrated circuit device **101** (corresponding to a second device) within information equipment **140** at the user, the encrypted program is decrypted by using a secret key and a decryption program.

The PC **128a** is a device at the program developer and keeps a program **D128a** and an encryption program **128b** for encrypting a program.

The information equipment **140** is equipment at the program user and has: the semiconductor integrated circuit device **101**; a flash memory **123a** for keeping a decryption program **D123a**; a USB upstream port **124**; and peripheral equipment **150**. An outer bus **102** provides connection among the semiconductor integrated circuit **101**, the flash memory **123a**, and the USB upstream port **124**.

The semiconductor integrated circuit device has: a CPU **103a**; internal RAMs **104** (corresponding to a first memory) and **105** (corresponding to a second memory); a public key storing register **106**; a bus port **110a**; a security controller **111a**; and an I/O port **122**. The internal bus **109** is connected in the manner as shown in the drawing.

The CPU **103a** has a general-purpose register controller **119a** and general-purpose

registers **120a**.

The security controller **111a** has a flag storing portion **113a** for storing a program decryption execute flag **112F** (corresponding to a second flag) and a RAM copy flag **113F** (corresponding to a first flag), a chip select dispatcher **114a**, and a DMA controller **118a**.

A specific description will be given to the respective contents and operations of the individual elements.

The external bus **102** is used to transfer a public key stored in the public key storing register **106** to the personal computer **128a** and transfer a program encrypted by using the public key and the encryption program **D128b** to the semiconductor integrated circuit device **101**.

The CPU **103a** operates in accordance with a program stored in the internal RAMs **104** and **105** or in the flash memory **123a**. The CPU **103a** not only operates a normal program but also decrypts an encrypted program and executes the decrypted program. The CPU **103a** also transfers the encrypted program inputted from the outside and the decryption program **D123a** to the internal RAM **104**.

The internal RAM **104** is a memory used during a normal operation, i.e., when either of the decryption program **D123a** and the decrypted program is not executed. A description will be given to the case where a program encrypted by using the public key and the encryption program **D128b** is decrypted and executed. First, the encrypted program and the decryption program **D123a** in the flash memory **123a** are transferred by the CPU **103a** to the internal RAM **104** in the state in which the external bus **102** and the internal bus **109** are connected to each other by the bus port **110a**. Then, after the bus port **110a** disconnects the external bus **102** and the internal bus **109** from each other, the encrypted program and the decryption program **D123a** are transferred by the DMA controller **118a** from the internal RAM **104** to the internal RAM **105**. Thereafter, the security controller

111a disables access from the internal bus **109** to the internal RAM **104** until the execution of the decrypted program is completed.

The internal RAM **105** is used during the execution of the decryption program **D123a** and during the execution of the decrypted program. A description will be given to the case where the encrypted program is decrypted and executed. After the bus port **110a** disconnects the external bus **102** and the internal bus **109** from each other, the encrypted program and the decryption program **D123a** are transferred by the DMA controller **118a** from the internal RAM **104** to the internal RAM **105**. In the state in which the external bus **102** and the internal bus **109** are connected to each other by the bus port **110a**, the security controller **111a** disables access from the internal bus **109** to the internal RAM **105**. Accordingly, the decrypted program temporarily stored in the internal RAM **105** and data during the execution of a decryption process are not monitored from the outside.

The public key storing register **106** is a register storing therein a public key, which is used only for reading. The public key is transferred to the personal computer **128a** disposed outside the semiconductor integrated circuit device **101** and used when the program **D128a** is encrypted in accordance with the encryption program **D128b**.

The secret key storing register **107** is a register storing therein a secret key, which is used only for reading. The secret key is used when the encrypted program is decrypted in accordance with the decryption program **D123a**.

The secret key access port **108a** enables the CPU **103a** to read the secret key from the secret key storing register **107** only while the RAM copy flag **113F** is reset. Specifically, the secret key access port **108a** enables the CPU **103a** to read the secret key from the secret key storing register **107** only while the program is decrypted, the decrypted program is executed after the decryption program **D123a** is initiated, the transfer of the encrypted program and the decryption program **D123a** from the internal RAM **104** to the

internal RAM **105** is completed, and the RAM copy flag **113F** is reset. At any time other than the above, the secret key access port **108a** disables the reading of the secret key.

The internal bus **109** is used to transfer a program and data within the semiconductor integrated circuit device **101**.

5 The bus port **110a** disconnects the internal bus **109** and the external bus **102** from each other if at least one of the program decryption execute flag **112F** and the RAM copy flag **113F** is set. Accordingly, the internal bus **109** and the internal RAM **105** are not monitored from the outside during the transfer of the encrypted program and the decryption program **D123a** and during the execution of the decryption program **D123a** and
10 the decrypted program. In any case other than the above, the internal bus **109** and the external bus **102** are connected to each other.

The security controller **111a** is internally provided with the flag storing portion **113a** for keeping the program decryption execute flag **112F** and the RAM copy flag **113F**, with the chip select dispatcher **114a**, and with the DMA controller **118**. The security
15 controller **111a** controls the bus port **110a**, the secret key access port **108a**, chip select signals **116S** and **117S**, and the general-purpose register controller **119a** in decrypting the program encrypted by using the encryption program **D128b** and the public key stored in the public key storing register **106** and executing the decrypted program.

A description will be given to the case where the program encrypted by the
20 encryption program **D128b** is decrypted and executed. First, when the encrypted program and the decryption program **D123a** are transferred by the CPU **103a** to the internal RAM **104** in the state in which the external bus **102** and the internal bus **109** are connected to each other by the bus port **110a**, the bus port **110a** then disconnects the external bus **102** and the internal bus **109** from each other. Then, the chip select dispatcher **114a** asserts the
25 chip select signals **116S** and **117S** such that the program encrypted by the DMA controller

118a and the decryption program D123a are transferred from the internal RAM 104 to the internal RAM 105. When the transfer is completed, the chip select dispatcher 114a negates the chip select signal 116S and then shifts to the control of the CPU 103a. When the program is decrypted in the CPU 103a and the execution of the decrypted program is completed, a completion notice is given to the chip select dispatcher 114a. Upon receipt of the notice, the chip select dispatcher 114a generates the chip select signal 117S, causes the general-purpose register controller 119a to initialize the general-purpose registers 120a, and outputs the chip select signal 115S from the CPU 103a as the chip select signal 116S. Thereafter, the bus port 110a connects the internal bus 109 and the external bus 102 to each other.

The program decryption execute flag 112F is set by the CPU 103a at the initiation of the decryption program D123a and reset by the CPU 103a at the completion of the execution of the decrypted program. The decryption program D123a is initiated, the transfer of the encrypted program and the decryption program D123a from the internal RAM 104 to the internal RAM 105 is completed, and the RAM copy flag 113F is reset. While the encrypted program is decrypted and the decrypted program is executed thereafter, access to the internal RAM 104 is disabled, while access to the internal RAM 105 and to the secret key storing register 107 is enabled. When the program decryption execute flag 112F is reset, access to the internal RAM 105 and to the secret key storing register 107 is disabled.

The RAM copy flag 113F is set by the CPU 103a at the initiation of the decryption program D123a and reset at the completion of data transfer from the internal RAM 104 to the internal RAM 105. Since the internal RAMs 104 and 105 are at the same location on a memory map, the respective chip select signals to the internal RAMs 104 and 105 are not normally asserted simultaneously. However, each of the chip select signals

116S and 117S from the chip select dispatcher 114a to the internal RAMs 104 and 105 is asserted by setting the RAM copy flag 113F when the encrypted program or the like is to be transferred from the internal RAM 104 to the internal RAM 105.

The chip select dispatcher (hereinafter referred to as "CS dispatcher") 114a asserts
5 each of the chip select signals 116S and 117S when the RAM copy flag 113F is set, thereby enabling the DMA controller 118a to transfer the encrypted program and the decryption program D123a from the internal RAM 104 to the internal RAM 105. When the program decryption execute flag 112F is set and the RAM copy flag 113F is reset, the CS dispatcher 114a negates the chip select signal 116S and transfers the chip select signal 115S as the
10 chip select signal 117S. This enables access to the internal RAM 105 during the decryption of the encrypted program and during the execution of the decrypted program. In any case other than those mentioned above, the CS dispatcher 114a transfers the chip select signal 115S as the chip select signal 116S and negates the chip select signal 117S, thereby disabling access to the internal RAM 105 during a normal operation, i.e., when either of
15 the decryption program D123a and the decrypted program is not executed.

The chip select signal 115S is outputted from the CPU 103a and asserted when the internal RAM 104 or the internal RAM 105 is to be accessed.

The chip select signals 116S and 117S are outputted from the CS dispatcher 114a. The chip select signal 116S is asserted when the internal RAM 104 is to be accessed. The
20 chip select signal 117S is asserted when the internal RAM 105 is to be accessed.

When the RAM copy flag 113F is set, the DMA controller 118a transfers the encrypted program and the decryption program D123a from the internal RAM 104 to the internal RAM 105. When the transfer is completed, the RAM copy flag 113 is reset.

The general-purpose register controller 119a resets the general-purpose registers
25 120a when the program decryption execute flag 112F is reset. During the decryption of the

encrypted program, therefore, data generated in the general-purpose registers **120a** during the execution of the decrypted program is not monitored from the outside.

The I/O port **122** is connected to the CPU **103a** via the I/O bus **121**. The I/O port **122** is also connected to an external circuit such as a sound module **151** or a video module
5 **152** in the peripheral equipment **150**.

The flash memory **123a** keeps the decryption program **D123a**.

The decryption program **D123a** is transferred to the internal RAM **105** via the internal RAM **104** within the semiconductor integrated circuit device **101** and used in conjunction with the secret key stored in the secret key storing register **107** when the
10 encrypted program is decrypted.

The USB upstream port **124** is connected to the personal computer **126** via a USB cable **125** and used to transfer the encrypted program to the semiconductor integrated circuit device **101**.

The USB cable **125** is used to transfer the encrypted program from the personal
15 computer **126** to the USB upstream port **124**.

The personal computer **126** receives the encrypted program from the personal computer **128a** and transfers the encrypted program to the information equipment **140** on which the semiconductor integrated circuit device **101** is mounted.

A network line **127** is used to transfer the encrypted program from the personal
20 computer **128** to the personal computer **126**.

The personal computer **128** receives the public key stored in the public key storing register **106** from the personal computer **126** via the network line **127**, encrypts the program **D128a** by using the encryption program **D128b** and the public key, and transfers the encrypted program to the personal computer **126** via the network line **127**.

25 The program **128a** is encrypted by using the encryption program **D128b** and the

public key stored in the public key storing register **106** and then transferred to the semiconductor integrated circuit device **101** via the network line **127**, the personal computer **126**, the USB cable **125**, the USB upstream port **124**, and the external bus **102**. The encrypted program **128a** is decrypted in the semiconductor integrated circuit device
5 **101** by using the decryption program **D123a** and the secret key stored in the secret key storing register **107**.

A reference numeral **D128b** denotes an encryption program for encrypting the program **D128a** by using the public key stored in the public key storing register **106**.

The information equipment **140** has: the semiconductor integrated circuit device
10 **101**; the peripheral equipment **150**; the flash memory **123a**; and the USB upstream port **124**.

The peripheral equipment **150** has: the sound module **151**; and the video module **152** and is connected to the I/O port **122** in the semiconductor integrated circuit device **101**.

The sound module **151** is connected to the I/O port **122** of the semiconductor
15 integrated circuit device **101** to perform reproduction, recording, and the like of a sound through the transmission and reception of transferred data and the reception of a control signal.

The video module **152** is connected to the I/O port **122** of the semiconductor
integrated circuit device **101** to perform reproduction of a dynamic picture image through
20 the transmission and reception of transferred data and the reception of a control signal.

Referring to FIG. 2, the outline of the procedure of decrypting the encrypted program to generate the program **D128a** and executing the program **D128a** will be described.

FIG. 2 is a flow chart showing the procedure of decrypting the encrypted program
25 in the first embodiment.

First, in Step ST201, the CPU **103a** transfers the decryption program **D123a** and the encrypted program to the internal RAM **104**.

When the transfer is completed, the whole process then advances to Step ST202 where the CPU **103a** sets the program decryption execute flag **112F** and the RAM copy flag **113F**. At this time, the bus port **110a** disconnects the internal bus **109** and the external bus **102** from each other.

After the disconnection, the whole process then advances to Step ST203 where the DMA controller **118a** transfers the decryption program **D123a** and the encrypted program in the internal RAM **104** to the internal RAM **105**.

When the transfer is completed, the whole process then advances to Step ST204 where the CPU **103a** resets the RAM copy flag **113F**. From the resetting of the RAM copy flag **113F** on till the completion of Step ST206, which will be described later, the CS dispatcher **114a** does not assert the chip select signal **116S**.

The whole process then advances to Step ST205 where the CPU **103a** executes the decryption program **D123a**, decrypts the encrypted program by using the secret key stored in the secret key storing register **107** to generate the program **D128a**, and writes the generated program **D128a** in the internal RAM **105**.

The whole process then advances to Step ST206 where the CPU **103a** executes the program **D128a**.

Finally, the whole process advances to Step ST207 where the CPU **103a** resets the program decryption execute flag **112F**. When the program decryption execute flag **112F** is reset, the general-purpose register controller **119a** resets the general-purpose registers **120a**. When the program decryption execute flag **112a** is reset, the bus port **110a** connects the internal bus **109** and the external bus **102** to each other, while the CS dispatcher **114a** outputs the chip select signal **116S** as the chip select signal **115S** and negates the chip

select signal **117S**.

Since the chip select signal **116S** is not asserted while the decryption program **D123a** is executed and the program **D128a** is generated, the data and program **D128a** under decryption are not stored in the internal RAM **104**. Since the chip select signal **117S** is negated while the external bus **102** and the internal bus **109** are connected to each other by the bus port **110a**, the data and program **D128a** under decryption is prevented from being monitored from the outside.

Thus, according to the first embodiment, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked.

EMBODIMENT 2

FIG. 3 is a block diagram showing a structure of a semiconductor integrated circuit device **301** according to a second embodiment of the present invention.

A semiconductor integrated circuit **301** shown in **FIG. 3** is different from the semiconductor integrated circuit device **101** shown in **FIG. 1** in that it further comprises a memory port **302** (corresponding to a first memory port) and a memory port **303** (corresponding to a second memory port). The semiconductor integrated circuit device **301** is also different from the semiconductor integrated circuit device **101** in that a security controller **111b** has only a flag storing portion **113b** for storing the program decryption execute flag **112F**. As for the other components, they operate similarly to the components shown in **FIG. 1** so that the description thereof will not be repeated.

The memory port **302** halts writing to the internal RAM **104** under the control of

the security controller when the program decryption execute flag **112F** is set. In other words, data cannot be written in the internal RAM **104** during the decryption of the program and during the execution of the decrypted program.

The memory port **303** halts access to the internal RAM **105** under the control of the security controller **111b** when the program decryption execute flag **112F** is reset. In other words, the internal RAM **105** cannot be accessed during the internal bus **109** and the external bus **102** are connected to each other by a bus port **110b**. Accordingly, the decrypted program and data during the execution of a decryption process, which are written in the internal RAM **105**, are not monitored from the outside.

A description will be given next to the procedure of decrypting the encrypted program to generate the program **D128a** and executing the program **D128a**.

FIG. 4 is a flow chart showing the procedure of decrypting the encrypted program in the second embodiment.

First, in Step ST201, a CPU **103b** transfers the decryption program **D123a** and the encrypted program to the internal RAM **104**.

When the transfer is completed, the whole process then advances to ST402 where the CPU **103b** sets the program decryption execute flag **112F**. At this time, the bus port **110b** disconnects the internal bus **109** and the external bus **102** from each other. The memory port **302** halts writing to the internal RAM **104**, while the memory port **303** enables access to the internal RAM **105**.

Then, the whole process advances to Step ST205 where the CPU **103b** executes the decryption program **D123a**, thereby decrypts the encrypted program by using the secret key stored in the secret key storing register **107** to generate the program **D128a**, and writes the generated program **D128a** in the internal RAM **105**.

Then, the whole process advances to Step ST206 where the CPU **103b** executes

the program **D128a**.

Finally, when the execution of the program **D128a** is completed, the whole process advances to Step ST207 where the program decryption execute flag **112F** is reset. When the program decryption execute flag **112F** is reset, the general-purpose register controller **119b** resets the general-purpose registers **120b** under the control of the security controller **111b**. When the program decryption execute flag **112F** is reset, the bus port **110b** connects the internal bus **109** and the external bus **102** to each other, while the memory port **302** enables writing to the internal RAM **104** and the memory port **303** halts access to the internal RAM **105**.

In the semiconductor integrated circuit device **301**, the memory port **302** executes the decryption program **D123a** and halts writing to the internal RAM **104** while the program **D128a** is generated so that the data and program **D128a** under decryption are not stored in the internal RAM **104**. In addition, the memory port **303** halts access to the internal RAM **105** while the external bus **102** and the internal bus **109** are connected to each other by the bus port **110b** so that the data and program **D128a** under decryption are not outputted to the outside.

Thus, according to the second embodiment, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked.

EMBODIMENT 3

FIG. 5 is a block diagram showing a structure of a semiconductor integrated circuit device **501** according to a third embodiment of the present invention.

A semiconductor integrated circuit device **501** shown in FIG. 5 is different from the semiconductor integrated circuit device **101** shown in FIG. 1 in that it further comprises a memory port **402**. The semiconductor integrated circuit device **501** is also different from the semiconductor integrated circuit device **101** shown in FIG. 1 in that a security controller **111c** has a flag storing portion **113c** for storing the program decryption execute flag **112F** and a RAM initializer **502** (corresponding to a memory initializer). As for the other components, they operate similarly to the components shown in FIG. 1 so that the description thereof will not be repeated.

Immediately before the program decryption execute flag **112F** is reset, the RAM initializer **502** writes "1" in each of the regions of the internal RAM **105** to erase data, thereby preventing the decrypted program and the data under decryption, which are written in the internal RAM **105**, from being monitored from the outside.

A description will be given next to the procedure of decrypting the encrypted program to generate the program **D128a** and executing the program **D128a**.

FIG. 6 is a flow chart showing the procedure of decrypting the encrypted program in the third embodiment.

First, in Step ST201, a CPU **103c** transfers the decryption program **D123a** and the encrypted program to the internal RAM **104**.

When the transfer is completed, the whole process then advances to ST402 where the CPU **103c** sets the program decryption execute flag **112F**. At this time, a bus port **110c** disconnects the internal bus **109** and the external bus **102** from each other, while the memory port **402** halts writing to the internal RAM **104** under the control of the security controller **111c**.

Then, the whole process advances to Step ST205 where the CPU **103c** executes the decryption program **D123a**, thereby decrypts the encrypted program by using the secret

key stored in the secret key storing register 107 to generate the program **D128a**, and writes the generated program **D128a** in the internal RAM 105.

When the generated program **D128a** is written in the internal RAM 105, the whole process then advances to Step ST206 where the CPU 103c executes the program **D128a**.

The whole process then advances to Step ST607 where the RAM initializer 502 writes "1" in each of the regions of the internal RAM 105 to erase data.

Finally, when the data in the internal RAM 105 is erased, the whole process advances to Step ST207 where the program decryption execute flag 112F is reset. When the program decryption execute flag 112F is reset, the general-purpose register controller 119c resets the general-purpose registers 120c under the control of the security controller 111b. When the program decryption execute flag 112F is reset, the bus port 110c connects the internal bus 109 and the external bus 102 to each other, while the memory port 402 enables writing to the internal RAM 104 under the control of the security controller 111c.

In the semiconductor integrated circuit device 501, the memory port 402 executes the decryption program **D123a** and halts writing to the internal RAM 104 while the program **D128a** is generated so that the data and program **D128a** under decryption are not stored in the internal RAM 104. In addition, the RAM initializer 502 has completely erased data in the internal RAM 105 immediately before the bus port 110c brings the external bus 102 and the internal bus 109 in the disconnected state into the connected state so that the data and program **D128a** under decryption are not outputted to the outside.

Thus, according to the third embodiment, it is no more necessary to provide the semiconductor integrated circuit device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are

not monitored from the outside. This reduces the probability that the encrypted program is hacked.

EMBODIMENT 4

FIG. 7 is a block diagram showing a structure of a semiconductor integrated circuit device **701** according to a fourth embodiment of the present invention.

A semiconductor integrated circuit device **701** shown in FIG. 7 is different from the semiconductor integrated circuit device **101** shown in FIG. 1 in that it further comprises a decryption key access port **703** and a decryption key storing register **702**. A PC **128d** is different from the PC **128a** shown in FIG. 1 in that it keeps a decryption key encryption program **D728c**, an encryption key **D728d**, and a decryption key **D728e** in addition to the program **D728a** and the encryption program **D728b**. A flag storing portion **113d** is different from the flag storing portion **113a** shown in FIG. 1 in that it keeps a decryption key decryption flag **704F** in addition to the program decryption execute flag **112F** and the RAM copy flag **113F**. A flash memory **123d** is different from the flash memory **123a** in that it keeps a decryption key decryption program **D723b** in addition to the decryption program **723a**. As for the other components, they operate similarly to the components shown in FIG. 1 so that a description will be given with particular emphasis on different portions between FIGS. 7 and 1.

A CPU **103d** operates in accordance with a program stored in the internal RAM **104** or **105** or in the flash memory **123d**. Besides operating a normal program, the CPU **103d** executes the decryption of the encrypted decryption key and the decryption of the encrypted program as well as the decrypted program. The CPU **103d** also transfers the encrypted decryption key inputted from the outside, the encrypted program, the decryption key encryption program **D723b**, and the decryption program **D723a** to the internal RAM

104.

The internal RAM 104 is a memory used during a normal operation, i.e., when none of the decryption program D723a, the decryption key decryption program D723b, and the decrypted program is executed. A description will be given to the case where the encrypted decryption key is decrypted and stored in the decryption key storing register 702.

- 5 First, in the state in which the external bus 102 and the internal bus 109 are connected to each other by the bus port 110d, the CPU 103d transfers the encrypted decryption key and the decryption key decryption program D723b in the flash memory 123d to the internal RAM 104 via the external bus 102 and the internal bus 109. Then, after the bus port 110d disconnects the external bus 102 and the internal bus 109 from each other, a DMA
10 controller 118d transfers the encrypted decryption key and the decryption key decryption program D723b from the internal RAM 104 to the internal RAM 105. Thereafter, a security controller 111d disables access from the internal bus 109 to the internal RAM 104 until the decryption key decryption program D723b is completed.

- Subsequently, a description will be given to the case where the encrypted program
15 is decrypted and executed. First, the CPU 103d transfers the encrypted program and the decryption program D723a to the internal RAM 104 in the state in which the external bus 102 and the internal bus 109 are connected to each other by the bus port 110d. After the bus port 110d then disconnects the external bus 102 and the internal bus 109 from each other, the DMA controller 118d transfers the encrypted program and the decryption
20 program D723a from the internal RAM 104 to the internal RAM 105. Thereafter, the security controller 111d disables access from the internal bus 109 to the internal RAM 104 until the execution of the decrypted program is completed.

- The internal RAM 105 is used during the execution of the decryption key decryption program D723b, the decryption program D723a, and the decrypted program
25 D728b. A description will be given to the case where the encrypted decryption key is

decrypted and stored in the decryption key storing register **702**. After the bus port **110d** disconnects the external bus **102** and the internal bus **109** from each other, the DMA controller **118d** transfers the encrypted decryption key and the decryption key decryption program **D723b** from the internal RAM **104** to the internal RAM **105**. During the decryption of the encrypted decryption key, the CPU **103d** decrypts the encrypted decryption key by using the internal RAM **105**. A description will be given to the case where the encrypted program is decrypted and executed. After the bus port **110d** disconnects the external bus **102** and the internal bus **109** from each other, the encrypted program and the decryption program **D723a** are transferred from the internal RAM **104** to the internal RAM **105**. During the decryption of the encrypted program and during the execution of the decrypted program, the CPU **103d** decrypts the encrypted program and executes the decrypted program by using the internal RAM **105**. While the external bus **102** and the internal bus **109** are connected to each other by the bus port **110d**, access from the internal bus **109** to the internal RAM **105** is disabled. Accordingly, the decrypted decryption key **D728e**, the decrypted program **D728a**, and data during the execution of these decryption processes, each temporarily stored in the internal RAM **105**, are not monitored from the outside.

The public key storing register **106** is a register storing a public key, which is used only for reading. The public key is transferred to the personal computer **128e** disposed outside the semiconductor integrated circuit device **701** and used in conjunction with the decryption key encryption program **D728c** to encrypt the decryption key **D728e**. The encrypted decryption key is decrypted by using the decryption key decryption program **D723b** and the secret key stored in the secret key storing register **107**.

The secret key storing register **107** is a register storing a secret key, which is used only for reading. The secret key is used when the encrypted decryption key is decrypted by

using the secret key.

The decryption key storing register **702** is a register for storing the decryption key **D728e** such that it is written therein and read therefrom. The decryption key **D728e** is used in conjunction with the decryption key decryption program **D723b** to decrypt the encrypted program.

The secret key access port **108d** enables the CPU **103d** to read the secret key from the secret key storing register **107** only while the decryption key decryption flag **704F** is set and the RAM copy flag **113F** is reset. Specifically, the CPU **103d** enables the reading of the secret key from the secret key storing register **107** only while the decryption key decryption program **D723b** is initiated, the transfer of the encrypted decryption key and the decryption key decryption program **D723b** from the internal RAM **104** to the internal RAM **105** is completed, the RAM copy flag **113F** is reset, and the encrypted decryption key is decrypted thereafter. At any time other than the above, the reading of the secret key is disabled.

The decryption key access port **703** enables the writing of the decryption key **D728e** while the decryption key decryption flag **704F** is set and the RAM copy flag **113** is reset. The decryption key access port **703** enables the reading of the decryption key **D728e** while the program decryption execute flag **112F** is set and the RAM copy flag **113F** is reset. At any time other than the above, the writing and reading of the decryption key **D728e** are both disabled. Specifically, the writing of the decryption key **D728e** is enabled while the decryption key decryption program **D723b** is initiated, the transfer of the encrypted decryption key and the decryption key decryption program **D723b** from the internal RAM **104** to the internal RAM **105** is completed, the RAM copy flag **113F** is reset, and the encrypted decryption key is decrypted thereafter. On the other hand, the reading of the decryption key **D728e** is enabled while the decryption program **D723a** is initiated, the

transfer of the encrypted program and the decryption program **D723a** from the internal RAM **104** to the internal RAM **105** is completed, the RAM copy flag **113F** is reset, and the encrypted program is decrypted thereafter.

The bus port **110d** disconnects the internal bus **109** and the external bus **102** from each other when at least one of the decryption key decryption flag **704F**, the program decryption execute flag **112F**, and the RAM copy flag **113F** is set. During the execution of the decryption key decryption program **D723b**, the decryption program **D723a**, and the decrypted program **D728a**, therefore, the internal bus **109** and the internal bus RAM **105** are not monitored from the outside. In any case other than the above, the internal bus **109** and the external bus **102** are connected to each other.

The security controller **111d** is internally provided with a flag storing portion for keeping the decryption key decryption flag **704F**, with the program decryption execute flag **112F**, and with the RAM copy flag **113F**, a CS dispatcher **114d**, and the DMA controller **118d**.

The decryption key decryption flag **704F** is set by the CPU **103** when the decryption key decryption program **D723b** is initiated and reset by the CPU **103** when the decryption of the decryption key is completed. The decryption key decryption program **D723b** is initiated, the transfer of the encrypted decryption key and the decryption key decryption program **D723b** from the internal RAM **104** to the internal RAM **105** is completed, and the RAM copy flag **113F** is reset. Thereafter, access to the internal RAM **104** is disabled during the decryption of the encrypted decryption key, while access to the internal RAM **105**, to the secret key storing register **107**, and to the decryption key storing register **702** is enabled. When the decryption key decryption flag **704F** is reset, access to the internal RAM **105**, to the secret key storing register **107**, and to the decryption key storing register **702** is disabled.

The program decryption execute flag **112F** is set by the CPU **103d** at the initiation of the decryption program **D723a** and reset by the CPU **103d** at the completion of the execution of the decrypted program. The decryption program **D723a** is initiated, the transfer of the encrypted program and the decryption program **D723a** from the internal RAM **104** to the internal RAM **105** is completed, and the RAM copy flag **113F** is reset. While the encrypted program is decrypted and the decrypted program is executed thereafter, access to the internal RAM **104** is disabled and access to the internal RAM **105** and to the decryption key storing register **702** is enabled. When the program decryption execute flag **112F** is reset, access to the internal RAM **105**, to the secret key storing register **107**, and to the decryption key storing register **702** is disabled.

The RAM copy flag **113F** is set by the CPU **103d** at the initiation of the decryption key decryption program **D723b** or the decryption program **D723a** and reset by the CPU **103d** at the completion of data transfer from the internal RAM **104** to the internal RAM **105**.

The CS dispatcher **114d** asserts each of the chip select signals **116S** and **117S** when the RAM copy flag **113F** is set, thereby enabling the DMA controller **118d** to transfer the encrypted decryption key, the decryption key decryption program **D723b**, the encrypted program, and the decryption program **D723a** from the internal RAM **104** to the internal RAM **105**. When the decryption key decryption flag **704F** or the program decryption execute flag **112F** is set and the RAM copy flag **113F** is reset, the CS dispatcher **114d** negates the chip select signal **116S** and transfers the chip select signal **115S** as the chip select signal **117S**. This enables access to the internal RAM **105** during the decryption of the encrypted decryption key, during the decryption of the encrypted program, and during the execution of the decrypted program. In any case other than those mentioned above, the CS dispatcher **114d** transfers the chip select signal **115S** as the chip select signal

116S and negates the chip select signal **117S**, thereby disabling access to the internal RAM **105** during a normal operation, i.e., when none of the decryption key decryption program **D723b**, the decryption program **D723a**, and the decrypted program **D728a** is executed.

When the RAM copy flag **113F** is set, the DMA controller **118d** transfers the
5 encrypted decryption key, the decryption key decryption program **D723b**, the encrypted program, and the decryption program **D723a** from the internal RAM **104** to the internal RAM **105**. When the transfer is completed, the DMA controller **118d** resets the RAM copy flag **113F**.

The general-purpose register controller **119d** resets the general-purpose registers
10 **120d** when the decryption key decryption flag **704F** or the program decryption execute flag **112F** is reset. During the decryption of the encrypted program, therefore, data generated in the general-purpose registers **120d** during the execution of the decrypted program is not monitored from the outside.

The decryption key decryption program **D723b** is kept in the flash memory **123d**.

15 When the decryption key encrypted by using the decryption key encryption program **D728c** and the secret key is decrypted, the decryption key decryption program **D723b** is transferred to the internal RAM **105** via the internal RAM **104** in the semiconductor integrated circuit device **701** to decrypt the encrypted decryption key in conjunction with the secret key stored in the secret key storing register **107**.

20 The decryption program **D723a** is kept in the flash memory **123d**. When the program encrypted by using the encryption program **D728b** and the encryption key **D728d** is decrypted, the decryption program **D723a** is transferred to the internal RAM **105** via the internal RAM **104** in the semiconductor integrated circuit device **701** to decrypt the encrypted program in conjunction with the decryption key stored in the decryption key
25 storing register **702**.

The program **D728a** is encrypted by using the encryption program **D728b** and the encryption key **D728d** and transferred to the semiconductor integrated circuit device **701** via the network **127**, the personal computer **126**, the USB cable **125**, the USB upstream port **124**, and the external bus **102**. In the semiconductor integrated circuit device **701**, the program **D728a** is decrypted by using the decryption program **D723a** and the decryption key **D728e** stored in the decryption key storing register **107**.

The encryption program **D728b** is for encrypting the program **D728a** by using the encryption key **D728d**.

The decryption key encryption program **D728c** is for encrypting the decryption key **D728e** in conjunction with the public key stored in the public key storing register **106**.

The encryption key **D728d** is for encrypting the program **D728a** in conjunction with the encryption program **D728b**.

The decryption key **D728e** is for decrypting the encrypted program by using the encryption key **D728d** in conjunction with the decryption program **D723a**.

Information equipment **740** has the semiconductor integrated circuit device **701**, the peripheral equipment **150**, the flash memory **123d**, and the USB upstream port **124**.

A description will be given next to the procedure of decrypting the encrypted decryption key and storing the decryption key **D728e** in the decryption key storing register **702**.

FIG. 8 is a flow chart showing the procedure of decrypting the encrypted decryption key in the fourth embodiment.

First, in Step ST801, the CPU **103d** transfers the decryption key decryption program **D723b** and the encrypted decryption key to the internal RAM **104**.

When the transfer is completed, the whole process then advances to Step ST802 where the CPU **103d** sets the decryption key decryption flag **704F** and the RAM copy flag

113F. At this time, the bus port **110d** disconnects the internal bus **109** and the external bus **102** from each other.

After the disconnection, the whole process then advances to Step ST803 where the DMA controller **118d** transfers the decryption key decryption program **D723b** and the encrypted decryption key in the internal RAM **104** to the internal RAM **105**.

When the transfer is completed, the whole process then advances to Step ST804 where the CPU **103d** resets the RAM copy flag **113F**. From the resetting of the RAM copy flag **113F** on till the completion of Step ST805, which will be described later, the CS dispatcher **114d** does not assert the chip select signal **116S**.

Next, the whole process advances to Step ST805 where the CPU **103d** executes the decryption key decryption program **D723b** by using the secret key stored in the secret key storing register **107** to decrypt the encrypted decryption key, thereby generates the decryption key **D728e**, and stores it in the decryption key storing register **702**.

Finally, the whole process advances to Step ST806 where the decryption key decryption flag **704F** is reset. When the decryption key decryption flag **704F** is reset, the general-purpose register controller **119d** resets the general-purpose registers **120d**. When the decryption key decryption flag **704F** is reset, the bus port **110d** connects the internal bus **109** and the external bus **102** to each other. The CS dispatcher **114d** transfers the chip select signal **115S** as the chip select signal **116S** and negates the chip select signal **117S**.

FIG. 9 shows the respective states of the decryption key decryption flag **704F**, the program decryption execute flag **112F**, the bus port **110d** corresponding to the state of the RAM copy flag **113F**, the secret key access port **108d**, the decryption key access port **703**, and the chip select signals **116S** and **117S**.

In FIG. 9, “Open” represents the case where the bus port **110d**, the secret key access port **108d**, and the decryption key access port **703** enable data transfer and “Close”

represents the case where data transfer is not enabled, while CS115 represents the case where the chip select signal **115S** is transferred as the chip select signals **116S** and **117S**.

As shown in FIG. 9, when the external bus **102** and the internal bus **109** are connected to each other by the bus port **110d**, the secret key storing register **107** and the decryption key decryption register **702** cannot be accessed. On the other hand, the chip select signal **116S** is not asserted when the decryption key decryption program **D723b** is executed and the decryption key **D728e** is generated. Accordingly, data under decryption, the secret key, and the decryption key **D728e** are not stored in the internal RAM **104**. Since the chip select signal **117S** is negated when the external bus **102** and the internal bus **109** are connected to each other by the bus port **110d**, data under decryption, the secret key, and the decryption key **D728e** are not outputted to the outside.

A description will be given next to the procedure of decrypting the encrypted program to generate the program **D728a** and executing the program **D728a** with reference to FIG. 10.

FIG. 10 is a flow chart showing the procedure of decrypting the encrypted program in the fourth embodiment.

First, in Step ST1001, the CPU **103d** transfers the decryption program **D723a** and the encrypted program to the internal RAM **104**.

When the transfer is completed, the whole process advances to Step ST1002 where the CPU **103d** sets the program decryption execute flag **112F** and the RAM copy flag **113F**. At this time, the bus port **110d** disconnects the internal bus **109** and the external bus **102** from each other.

After the disconnection, the whole process advances to Step ST1003 where the DMA controller **118d** transfers the decryption program **D723a** and the encrypted program in the internal RAM **104** to the internal RAM **105**.

When the transfer is completed, the whole process advances to Step ST1004 where the CPU **103d** resets the RAM copy flag **113F**. From the resetting of the RAM copy flag **113F** on till the completion of Step ST1006, which will be described later, the CS dispatcher **114d** does not assert the chip select signal **116S**.

5 Then, the whole process advances to Step ST1005 where the CPU **103d** executes the decryption program **D723a** by using the decryption key **D728e**, thereby decrypts the encrypted program, and generates the program **D728a**. The generated program **D728a** is written in the internal RAM **105**.

10 Then, the whole process advances to Step ST1006 where the CPU **103d** executes the program **D728a**.

15 Finally, the whole process advances to Step ST1007 where the CPU **103d** resets the program decryption execute flag **112F**. When the program decryption execute flag **112F** is reset, the general-purpose register controller **119d** resets the general-purpose registers **120d**. When the program decryption execute flag **112F** is reset, the bus port **110d** connects the internal bus **109** and the external bus **102** to each other. The CS dispatcher **114d** transfers the chip select signal **115S** as the chip select signal **116S** and negates the chip select signal **117S**.

20 As shown in FIG. 9, the chip select signal **116S** is not asserted when the decryption program **D723a** is executed and the program **D728a** is generated. Accordingly, data under decryption, the decryption key **D728e**, and the program **D728a** are not stored in the internal RAM **104**. Since the chip select signal **117S** is negated when the external bus **102** and the internal bus **109** are connected to each other by the bus port **110d**, data under decryption, the decryption key **D728e**, and the program **D728a** are not outputted to the outside.

25 Thus, it is no more necessary to provide the semiconductor integrated circuit

device with an internal nonvolatile memory for keeping the decryption program so that a cost reduction is achieved. Moreover, the encrypted program can be decrypted and executed, while the program and data under decryption are not monitored from the outside. This reduces the probability that the encrypted program is hacked.

5 In addition, the encryption program and the encryption strength can be selected at the encrypted program transferor.

- Program Delivery Method and System -

FIGS. 11 to 17 are views for illustrating a program delivery system and a program delivery method, which will be described herein below by using the present fourth
10 embodiment as an example.

FIGS. 11 to 17 show data transmission and reception between the semiconductor integrated circuit device **701** (corresponding to a second device) within information equipment used by the program user and the PC **128d** (corresponding to a first device) used by the program developer from the encryption of a program till the decryption of the
15 encrypted program.

First, as shown in FIG. 11, the semiconductor integrated circuit device **701** at the user transfers a public key **D106** stored in the public key storing register **106** to the PC **128d** at the developer.

Next, as shown in FIG. 12, the PC **128d** at the developer encrypts the decryption
20 key **D728e** by using the public key **D106** and the decryption key encryption program **D728c** to generate an encrypted decryption key **1201**.

Next, as shown in FIG. 13, the PC **128d** at the developer transfers the encrypted decryption key **1201** to the semiconductor integrated circuit device **701** at the user.

Next, as shown in FIG. 14, the semiconductor integrated circuit device **701** at the
25 user decrypts the encrypted decryption key **1201** by using the secret key **D107** stored in the

secret key storing register **107** and the decryption key decryption program **D723b** and stores the decryption key **D728e** in the decryption key storing register **702**.

Then, as shown in FIG. 15, the PC **128d** at the developer encrypts the program **D728a** by using the encryption key **D728d** and the encryption program **D728b** to generate an encrypted program **1501**.

Next, as shown in FIG. 16, the PC **128d** at the developer transfers the encrypted program **1501** to the semiconductor integrated circuit device **701** at the user.

Finally, as shown in FIG. 17, the semiconductor integrated circuit device **701** at the user decrypts the encrypted program **1501** by using the decryption key **D728e** and the decryption program **D723a** and executes the decrypted program **D728a**.

Thus, the program is encrypted by using the encryption key possessed by the program developer and the encrypted program is delivered to the user. Since the encrypted program can be decrypted by using the decryption key possessed by the program developer, it becomes possible to encrypt the program with an encryption strength desired by the program developer and deliver the encrypted program.

Although each of the first to fourth embodiments has described the case where the control of the internal RAMs **104** and **105** is effected by using the chip select signals in the semiconductor integrated circuit, it will easily be appreciated that the present invention is also similarly practicable in each of the embodiments even if a write enable signal and a read enable signal are used.